HDV130/100 Upgrade Firmware Via Abyss Web Server

March 10 2015

Installar

Executar abwsx1.exe



| byss Web Server X1 Setup: Installing | | |
|--|--|--------------------|
| Running Abyss Web Server Startup Configuration tool | Abyss Web Server | |
| Setup has completed. Start Abyss Web Server now? | Press OK to continue with the console acce | ess configuration. |
| Yes No Cancel Version 2.9.3.6 < Back Close | | |
| E Language - Windows Internet Explorer | | |
| 🔄 😔 = 🦉 http://127 🔎 💌 🖄 🍫 🗶 🥥 Language | × | 6 🛠 🗄 |
| Eile Edit View Favorites Tools Help | | |
| 🟠 🔹 🔂 🔹 🖃 🔹 Page 🔹 Safety 🕶 Tools 👻 🔞 🕶 | | |
| Language | | |
| Abyss Web Server Console :: Console Configuration :: Language | | Help |
| Choose the languag ید آن تستعملها. Choisissez la langue qu | e you want to use. احتر اللغة التي i e vous voulez utiliser. English عربية Fra r | ıçais |

| Access Credentials - Windows Internet Explorer | |
|--|------------------|
| Contentials | 6 🕁 😳 |
| e Edit View Favorites Iools Help | |
|) ▼ 🖾 ▼ 🖻 🖶 ▼ Page ▼ Safety ▼ Tools ▼ 🔞 ▼ | |
| Access Credentials | |
| Abyss Web Server Console :: Console Configuration :: Access Credentials | Help |
| Please enter a login and a password. You will use them to auth <u>enticate yourself eventime you acc</u> | are the concole |
| Login : psn | |
| Password : •••••• | |
| Password Again : Password : nsn0101 | |
| Your browser will ask you to enter the new login and password after pressing OK. | |
| | OK Cancel |
| | |
| Windows Security X The server 127.0.0.1 at Abyss Web Server Console requires a username and password. Warning: This server is requesting that your username and password be sent in an insecure manner (basic authentication without a secure connection). | |
| Entre Logi Remember my credentials | in and Password. |
| OK Cancel | |

Altere configuração de Firewall no PC.

Control Panel -> Network and Sharing Center -> Windows Firewall -> Allow a program or feature through Windows Firewall



| 💮 Control Panel\Al | Control Panel Items\Windows Firewall\Allowed Programs | | <u>-0×</u> |
|----------------------|--|--|-------------|
| ○ | Control Panel + All Control Panel Items + Windows Firewall + Allowed Programs | 👻 🚱 Search Co | ntrol Panel |
| G → • • • • • | Control Panel Allow programs to communicate through Windows Firewall To add, change, or remove allowed programs and ports, click Change settings. What are the risks of allowing a program to communicate? Allowed programs and features: Name Allowed programs and features: Allowed programs and features | Kearch Co Search Co Search Co Charges Home/Work (Private) Pul Detai(s Rep Allow another proc | ntrol Panel |
| | | ок | ancel |

Add a Program

Select the program you want to add, or click Browse to find one that is not listed, and then click OK.

×

Programs:

| | · · · · · · · · · · · · · · · · · · · | |
|-------------|--|---------------------------|
| Abyss | Web Server X1 | |
| Create | e a System Repair Disc | |
| C cyglau | i <mark>nc</mark> h | |
| Intern | et Explorer | |
| Micros | oft Virtual PC | |
| Je Mozilla | Firefox | |
| S Open(| Office | |
| Open | Office Base | |
| Open | Office Calc | |
| Open | Office Draw | |
| Datta | Cullaburg Web Converteburgers | Brownea |
| eu. | C: ADYSS WED SERVER ADYSSWS.EXE | Drowsen |
| Vhat are th | e risks of unblocking a program? | |
| | | 1999 (1999) (1999) (1999) |
| ou can cho | ose which network location types to add this | program to. |
| | O SAMA MA IN CONTRACTOR | |



2- Atualizar o HDV130/100

Atualizar o HDV130/100

• To manually update the firmware

Coloque o novo FW (2 arquivos abaixo)

HDV130-11.180.fw.part1

HDV130-11.180.fw.part2

na pasta: "C:\Abyss Web Server\htdocs"

Execute o Abyss Web Server.

(resetar o HDV para config de fábrica: >Menu> Config [#] [1] [3] [6])

Acesse o HDV1300/100, e em "Maintenance / Upgrade Firmware", preencha na URL:

http://192.168.0.33:8000/HDV130-11.180.fw.part1 ("IP do PC com o Abyss Web Server/arquivo")

| C:\Abyss Web Server\ | itdocs | | | KX-HDV130 - Windows Intern | net Explorer |
|---------------------------|--|-------------------|---------------|---|---|
| | | | | - 🔾 🔍 🔻 遵 http://192.168.0 | .200/ P 🛛 🔄 🎸 🗶 🎯 KX.HDV130 🛛 🗙 |
| Compute | er 🔹 Local Disk (C:) 🔹 Abyss Web Server 👻 htdocs | | | Eile Edit <u>V</u> iew Favorites <u>T</u> o | ools <u>H</u> elp |
| Organize 🔻 Include in lib | orary 🔻 Share with 🔻 Burn New folder | | | 🟠 • 🖾 · 🖻 👼 • Page • | Safety + Tgols + 🔞 + |
| Favorites | Name * | Date modified | Туре | Panasonic | |
| 📃 Desktop | index.html | 3/10/2015 2:47 PM | HTML Document | KX-HDV130 | Status Network System VoIP Telephone Maintenance |
| Download;s | 🔙 pwrabyss.gif | 3/10/2015 2:47 PM | GIF image | | Upgrade Firmware |
| 🔛 Recent Places | HDV130-01.008.fw | 3/3/2015 12:31 PM | FW File | Web Port Close | |
| 🔚 Libraries | | | | | |
| Documents | | | | Maintenance | I Ingrade Firmware |
| A | | | | Provisioning | Firmware File URL http://192.168.0.150/HDV130-01.008.fw |
| | | | | Maintenance Firmware Maintenance | |
| | | | | Import Configuration File | odate Firmware |
| | | | | Export Configuration File | |
| | | | | Export Operational Value | |
| | | | | Upgrade Firmware | http://192.168.0.33:8000/HDV130-11.180.fw.part1 |
| | | | | Import IP Phone | |
| | | | | Language | |
| | | | | Import Certificate File | |
| | | | | Export Logging File | |
| | | | | Open SSH Port | |
| | | | | Peer to Peer Mode | |
| | | | | Reset to Defaults | |

Atualizar o HDV130/100

Upgrade Firmware

Maintenance -> Upgrade Firmware

| Panasonic | |
|--|--|
| KX-HDV130 | Status Network System VolP Telephone Maintenance |
| Web Port Close | Upgrade Firmware |
| Maintenance Provisioning Maintenance | Upgrade Firmware Firmware File URL http://192.168.0.150/HDV130-01.008.fw |
| Firmware Maintenance Import Configuration File Export Configuration File Export Operational Value Upgrade Firmware Import Logo File | Update Firmware Clique "Update Firmware" |
| Import IP Phone Language Import Web Language Import Certificate File | lique "Upgrade Firmware" |
| Open SSH Port Peer to Peer Mode Reset to Defaults | O HDV irá reiniciar automaticamente após o processo. Update irá iniciar após a tela mostrar "ERASING **%" O HDV irá baixar o EW, apagar a memória e reescrever |
| | Irá reiniciar novamente. Pronto: Atualizado. Procedimento leva ~6min. |

Atualizar o HDV130/100

